

Ventey's TerraWave Dual Band Micro Omni MIMO Antenna is optimized for small form factor/aesthetic and mobile Wi-Fi applications. This aesthetically-pleasing antenna includes four dual-band Wi-Fi pigtails and RPTNC connectors. The antenna is an ideal partner for four connector dual-band Wi-Fi access points where low profile and/or aesthetics is a major deployment consideration. This multi-use antenna can also be used in vehicles for communications, location tracking, and fleet management. Every TerraWave antenna is covered by the company's two-year TerraNet warranty program. For more information, contact a regional sales executive at 210-375-8482, 800-851-4965 or sales@terrawave.com, or visit www.terrawave.com.




Specifications		
Model	M6025040O3D402MW	
Frequency Range	2400-2500 MHz	4900 - 5850 MHz
Bandwidth	100 MHz	950 MHz
Gain	2.5 dBi	4 dBi
VSWR	≤2	≤2
Impedance	50 ohms	
Polarization	Vertical	
Power	50 watts	
Connector	RPTNC male	
Port number	4	
Size	3.54" x 1.57"	
Weight	4.4 oz	
Operating Temperature	-40° F to +158° F	
Mounting Method	Surface Mount	

www.terrawave.com 1-800-851-4965




Installation

Outdoor Car Roof Installation



Indoor Ceiling Mount Installation




Note: The TerraWave SKU 509824 provides an L-Bracket mounting alternative for mast or wall mounting (sold separately)


www.terrawave.com 1-800-851-4965




Radiation Patterns


Port 1: 2450MHz







Port 1: 5500MHz





Port 2: 2450MHz







<u>www.terrawave.com</u> sales@terrawave.com 1-800-851-4965





Port 2: 5500MHz







Port 3: 2450MHz





Port 3: 5500MHz






<u>www.terrawave.com</u> sales@terrawave.com 1-800-851-4965



Port 4: 2450MHz





H Plane

-120 -150 -180

E Plane

Port 4: 5500MHz





E Plane

<u>www.terrawave.com</u> sales@terrawave.com 1-800-851-4965