

This portion of the manual covers the following models:

• **RZ250W** (Requires Z955W)

Congratulations on purchasing a PRO1 Wireless Zoning System.

This remote sensor was designed to the highest reliability and ease of use standards. Thank you for choosing Pro1.

Table of Contents	Page
Quick Reference	2
Establishing Communication	3
Installation Tips	4
Specifications & Contact Info	5



Caution:

Equipment damage hazard Do not operate the cooling system if the outdoor temperature is below 50° F (10° C) to prevent possible compressor damage.

A trained, experienced technician must install this product.

Carefully read these instructions. You could damage this product or cause a hazardous condition if you fail to follow these instructions.


Una versión española de este manual puede ser descargada en www.pro1iaq.com


Need Help?

For assistance with this product please visit http://www.pro1iaq.com or call Pro1 Customer Care toll-free at 888-Pro1iaq (776-1427) during normal business hours (Mon-Fri 9 AM - 6 PM Eastern)

Installing Batteries

To install 2 AA batteries remove the three screws shown in the diagram. One in the middle of the inside cover box, and two on either side of the cover box.







Note about low batteries:

When the outdoor battery needs to be changed the **Z955W Master Thermostat** will flash **LOW BAT OUTDOOR** as seen on the left.

PRO1 TIP and this RZ250W

Before putting the inside cover back on, proceed to the next page to establish a connection between the **Z955W Master Thermostat**

ESTABLISHING COMMUNICATION

Remember

The PRO1 Wireless Zoning System contains selectable wireless communication. Each component has a jumper switch label FSK and ASK. Default setting: FSK.

All components must be set to the same position for wireless communication.


(*ASK is required to connect to a T955W or T955WH.)

Inside of RZ250W FSK/ ASK Switch

Connecting to the Master Thermostat

Easy, two step communication link set up.

- The Z955W Master Thermostat Tech setting for the outdoor remote sensor must be set to YES. See the Z955W manual for instructions.
- While the Z955W is on the Outdoor Sensor screen hold down the connection button on the inside of the Outdoor Remote until the Z955W shows the letters YE and says Found Outdoor.



Connection button located inside the **RZ250W**



Example Step 2.

The Z955W, T955W, & T955WH Found Outdoor Screen.

Important:


DO NOT press the connection button again after Step 2 above has been completed. Pressing the button a second time will break the communication link and the connection steps will have to be repeated.

PRO1 TIP

For installations where the temperature will be frequently below freezing, battery life may be much better with 2 AA lithium batteries.



Range between the RZ250W and the Z955W master thermostat is approximately100 feet with no obstructions and approximately 50 feet in standard residential metal, brick, and concrete construction.



SPECIFICATIONS & CONTACT INFORMATION

Specifications

Temperature Range	-4° to 140°F (-20° to 60°C)
Temperature accuracy	± 1°F
Power source	Battery Power from 2 AA 1.5 V Batteries
Transmission	Every 5 minutes
Frequency	916 MHz

Contact Us

Pro1 IAQ Inc.

1111 S. Glenstone Suite 2-100 Springfield, MO 65804

Toll-free: 1-888-Pro1iaq (776-1427)

Toll Number (Outside the USA): 330-821-3600

Web: http://www.pro1iaq.com

Hours of Operation: Monday - Friday 9 AM - 6 PM Eastern